



©	
m	
Series <b>56</b>	



### **VALVE CONFIGURATIONS AVAILABLE**

- 3-Way Normally Open or Normally Closed (solenoid or remote air).
- 2-Way (by plugging a port) Normally Open or Normally Closed (solenoid or remote air).
- Internal pilot or External pilot for vacuum to 25 PSI main valve pressures on solenoid or remote air models.
- Manual and mechanical operators available.

## SERIES FEATURES-REMOTE AIR PILOT OPERATED VALVES

These remote air versions feature:

- A large checked accumulator for air/spring return.
- Balanced spool unaffected by back pressure in the exhaust or by inlet restrictions. May be plugged for 2-way operation.
- Use on lube or non-lube service.
- Optional remote air pilot, pilot operated models available when application requires a pilot signal below the main valve pressure.

### **APPLICATION CONVERSION PROCEDURE**

The balanced spool design and the unique N.C. and N.O. pilot valve function plate on solenoid models facilitate using the same valve for 7 different functions. The 7 functions are as follows:

- 3-way Normally Closed-All 3 main valve ports utilized and function plate placed with "3N.C." (3-way N.C.) visible.
- 3-way Normally Open-All 3 main valve ports utilized and function plate placed with "3N.O." (3-way N.O.) visible.

- 2-way Normally Closed-Same as 3-way N.C. but also plug port #3.
- 2-way Normally Open-Same as 3-way N.O. but also plug port #3.
- Selector-Pipe higher pressure to port #1 and lower pressure port #3.
- Internal Pilot-Utilized for main valve pressures of 25-150 PSI. Includes a check rod in the body and a 1/8'' pipe plug installed in the External Pilot port.
- External Pilot-An External Pilot supply is required when main valve pressures are lower than 25 PSI. If converting from an Internal Pilot model, remove the 1/8" pipe plug and check rod from the External Pilot port and install a 1/16" pipe plug in the check rod hole and pipe an external supply greater than 25 PSI to the External Pilot port. For vacuum service, make the vacuum connection to the port #3 and leave port #1 open to atmosphere or pressure port #1 for vacuum/pressure selector applications.

## **N.C.-N.O. OPERATIONS: SOLENOID MODELS:**

With the pilot valve available either N.C. or N.O., simply by inverting the function plate, maximum flexibility is available in solenoid pilot operated models by using the N.C. main spool and installing the function plate for either N.C. or N.O. operation. Where an N.C. pilot function is desired with a N.O. main valve operation, a N.O. main spool option is available.

#### **REMOTE AIR MODELS:**

On remote air pilot operated models, N.C. and N.O. main spools are both available so that a N.C. pilot signal can always be used.



Function	Port size	Flow (Max)	Individual n	nounting	Series
3/2 NO-NC, 2/2 NO-NC	3/8" - 1/2" -	3/4″ 5.7 C <sub>v</sub>	inline		
OPERATIONAL BENEFITS					
1. Balanced spool, immune to variatio pressure.	8. Pilot	ing effect eliminates sticking. valve with balanced poppet, high	n flow,		35
<ol> <li>Short stroke with high flow.</li> <li>Large spool area provides maximum</li> </ol>		t and consistent response times.			
forces.	aximum				100

- 4. Checked accumulator guarantees maximum pilot pressure.
- 5. Powerful return force thanks to the combination of mechanical and air springs.
- 6. Bonded spool with minimum friction, shifting in a glass-like finished bore.

## HOW TO ORDER

Port size	Pilot air	NC only valve	NO on	y valve
		NC pilot - NC spool	NO pilot - NC spool	NC pilot - NO spool
3/8″ NPTF		56C-12- <b>XXYZZ</b>	56C-22- <b>XXYZZ</b>	56C-62- <b>XXYZZ</b>
1/2" NPTF	Internal	56C-13- <b>XXYZZ</b>	56C-23- <b>XXYZZ</b>	56C-63- <b>XXYZZ</b>
3/4" NPTF		56C-17- <b>XXYZZ</b>	56C-27- <b>XXYZZ</b>	56C-67- <b>xxyzz</b>
3/8″ NPTF		56C-32- <b>XXYZZ</b>	56C-42- <b>XXYZZ</b>	56C-72- <b>xxyzz</b>
1/2″ NPTF	External	56C-33- <b>XXYZZ</b>	56C-43- <b>XXYZZ</b>	56C-73- <b>xxyzz</b>
3/4″ NPTF		56C-37- <b>XXYZZ</b>	56C-47- <b>XXYZZ</b>	56C-77- <b>xxyzz</b>

## SOLENOID OPERATOR ►

SOLENC	DID OPERATOR >		<u>XX Y ZZ</u>		900
XX	Voltage	Y	Manual operator	ZZ Electrical	connection 82
11	120/60, 110/50	1	Non-locking	JB Rectangular co	onnector
12	240/60, 220/50	2	Locking	JD Rectangular co	onnector with light
22	24/60, 24/50		-	JA Square connec	ctor 63
59	24 VDC (2.5 W)			JC Square connec	ctor with light
87	24 VDC (17.1 W)			BA Flying leads (1	18")
61	24 VDC (8.5 W)			CA Conduit 1/2"	NPS 65

\* Other options available, see page 349.

**MAC 250A MAC 500A** 

200

55 56 57

6600

1300

800

**ISO 1** 150 2 **ISO 3 MAC 125A** 





Fluid :	Compressed air, vacuum, inert gases
Pressure range :	Internal pilot : 25 to 150 PSI
	External pilot : vacuum to 150 PSI
Pilot pressure :	25 to 150 PSI
Lubrication :	Not required, if used select a medium aniline point lubricant (between 180°F and 210°F)
Filtration :	40 µ
Temperature range :	0°F to 120°F (-18°C to 50°C)
Flow (at 6 bar, $\Delta P=1bar$ ) :	Norm. Closed :3/8" (4.4 C <sub>v</sub> ), 1/2" (5.0 C <sub>v</sub> ), 3/4" (5.4 C <sub>v</sub> ), Norm. Open : 3/8" (4.6 C <sub>v</sub> ), 1/2" (5.1 C <sub>v</sub> ), 3/4" (5.7 C <sub>v</sub> )
Coil :	General purpose class A, continuous duty, encapsulated
Voltage range :	-15% to +10% of nominal voltage
Protection :	Consult factory
Power :	~ Inrush : 14.8 VA Holding : 10.9 VA
	= 1 to 17 W
Response times :	24 VDC (8.5 W) Energize : 11 ms De-energize : 10,8ms
	120/60 Energize : 7-12 ms De-energize : 9-14 ms
Spare parts :	<ul> <li>Solenoid operator (power ≥ 4 W) : D1-XXAA, cover mounting screws 32184 and seal 16234.</li> <li>Pilot valve : 130B-XXYZZ, including function plate A2-7009.</li> <li>Pilot mounting screws kit : N-56002.</li> </ul>
	• Check valve : 70063.
Options :	• BSPP threads.
DIMENSIONS	Dimensions shown are metric (m







CC

JA

JB JJ ЈМ Square Plug-in

Rectangular Plug-in Square Male only

Rectangular Male only

Non-locking Extended

Locking Extended

3

4



## Codification table for voltages / Manual operator / Electrical connection / Wire length

<b>OPTIONS AVAILABLE FOR</b>	OPTIONS AVAILABLE FOR
valves type 100 Series pilot valves "CNOMO"	- valves type 200 Series
Pilot operated valves with pilots type 100 Series Series : 55 - 56 - 700 - 800 - 900 - 6300 - 6500 - 6600 - 1300 - ISO 1 - ISO 2 - ISO 3. - MAC 125 - MAC 250 - MAC 500	- pilot operated valves with pilots type 200 Series Series : 200 - 57 - 58 - 59.



	00, 55, 56, 700, 800, 900, 6300, 6500, 6600, 1300, MVA1C 125, MAC250, MAC500.	C, Used on valve series: 2	200, 57, 58, 59.
	1. VOLTAGE (100 Serie type coil)		1. VOLTAGE (200 Serie type coil)
XX Y ZZ	VOLTAGE	- XX Y ZZ	VOLTAGE
11	120/60, 110/50	11	120/60, 110/50, 24 VDC (6 W)
12	240/60, 220/50	12	240/60, 220/50
13	100/60, 100/50	13	100/60, 100/50
15	200/60, 200 /50	14	200/60, 200/50
16	10/60	20	6/60
20	6/60	21	12/60
21	12/50, 12/60	22	24/60, 24/50
22	24/60, 24/50	23	32/60, 32/50
23	32/60, 32/50	24	48/60, 42/50
24	48/60, 42/50	25	240/50
26*	380/50, 440/50, 440/60, 480/60	26	480/60, 440/50
29	220/60	27	127/60
34	127/50, 120/50	28	415/50
35	48/50	29	220/60
36	16/60	30	380/50
B1	24/50	31	550/60, 550/50
50	24/30 24 VDC (6 W)	32	120/60, 110/50
50 51	24 VDC (6 W) 24 VDC (4 W)	33	600/60
54	12 VDC (4 W)	<u> </u>	127/50
55	12 VDC (4 W) 12 VDC (6 W)	<u> </u>	48/50
55 57		<u>50</u>	24 VDC (6 W)
57 59	12 VDC (2.5 W)	<u> </u>	24 VDC (8 W) 24 VDC (4.5 W)
59 60	24 VDC (2.5 W) 12 VDC (8.5 W)	52	24 VDC (4.5 W) 24 VDC (2.5 W)
61 64	24 VDC (8.5 W)	53	24 VDC (1.0 W)
	6 VDC (6 W)	55	12 VDC (6 W)
55 66	32 VDC (7 W)	57	12 VDC (2.5 W)
66 67	48 VDC (5.8 W)	<u> </u>	48 VDC (2.5 W)
67 49	64 VDC (7.5 W)	60	12 VDC (9.5 W)
68 60*	120 VDC (6.4 W)	61	24 VDC (8.5 W)
69* 75	220 VDC (8.7 W), 250 VDC (11.2 W)	64	6 VDC (8.5 W)
75	90 VDC (8.8 W)	<u> </u>	32 VDC (10 W)
76*	100 VDC (6.9 W)	66	48 VDC (11.5 W)
34*	125 VDC (10.9 W)	67	64 VDC (10.5 W)
87* 	24 VDC (17.1 W)	68	120 VDC (12.3 W)
88*	12 VDC (17.4 W)		250 VDC (9.2 W)
89*	36 VDC (18.8 W)		8 VDC (8.2 W)
90	28 VDC (8.2 W)	72	24 VDC (12 W)
91*	6 VDC (10.6 W)	73	198 VDC (10 W)
92	190 VDC (6.5 W)	74	72 VDC (11.3 W)
94	3 VDC (7 W)	75	90 VDC (11.3 W)
95	38 VDC (6.4 W)	76	100 VDC (9 W)
A1	24 VDC (1 W)	77	220 VDC (10 W), 230 VDC (11.6 W)
A2	12 VDC (1 W)	78*	24 VDC (24 W)
A3	9 VDC (1 W)	80	55 VDC (10.6 W)
OD. DD01 : Prote	ection diode (DC) - MAX. 8.5W	82	170 VDC (11.1 W)
	tection varistor (AC) - MAX. 8.5W	83	15 VDC (8.1 W)
Voltages are CLS	Fonly	84	125 VDC (10 W)
		86	36 VDC (11 W)

86

93\*

36 VDC (11 W)

12 VDC (24 W)



0					
0	n		1	0	n
0	P	1		0	

S

# 2. MANUAL OPERATOR (Common options for 100 & 200 Series type coils)

- XX Y ZZ	MANUAL OPERATOR		
0	No operator	5*	No Operator with Light
1	Non-locking recessed	6*	Non-Locking Recessed with Light
2	Locking recessed	7*	Locking Recessed with Light
3	Non-locking extended	8*	Non-Locking Extended with Light
4	Locking extended	9*	Locking Extended with Light
		• 11 1.	

\* Lights used with "AA" electrical connection

## 3. ELECTRICAL CONNECTION (100 Serie type coil)

3. ELECTRICAL CONNECTION (200 Serie type coil)

XX Y	ZZ	ELECTRICAL CONNECTION	- XX Y	ZZ	ELECTRICAL CONNECTION
	AA	Wiring box with 1/2" NPS conduit		AA	Wiring box with 1/2" NPS conduit
	BA	Flying leads		BA	Flying leads
	СА	1/2" NPS conduit		СА	1/2" NPS conduit
	СС	1/2" NPT conduit		СС	1/2" NPT conduit
	FA	Military type 2 PIN		EA	Explosion proof (200 Series)
	GA	Military type 3 PIN		EA	Explosion proof (57, 58 & 59 Series)
	HA	AA with ground wire		FA	Military type 2 PIN
	JA*	Square connector		GA	Military type 3 PIN
	JB	Rectangular connector		HA	AA with ground wire
	JC*	Square connector with light		JA*	Square connector
	JD	Rectangular connector with light		JC	Square connector with light
	JE	Square connector on top		JJ	Square connector, male only
		(ISO2, ISO3)		NA	CA with ground wire
	JF	Rectangular connector on top		NC	CC with ground wire
		(ISO1, ISO2, ISO3)			
	JG	JE with light			
	JH	JF with light			
	JJ	Square connector, male only			
	JM	Rectangular connector, male only			
	MA	Electrical common conduit			
		(100 Series-Manifold/900 Series)			
		-I ; I I ;			

МВ	Electrical common conduit
	(100 Series-Stacking/700 Series)
NA	CA with ground wire
NC	CC with ground wire
RA	3/8" NPS conduit

\* Not to be used with 100, 800 and 900 Series manifold mounting



XX Y ZZ (-VV)	WIRE LENGTH
AA	18″
AB	24"
AD	36″
AE	48″
AF	72"
AG	6″
AR	12"
AU	120″
BA	60″
BB	144″
eries 6000 : wire length, from	n the base
MOD L024	24"
MOD L036	36″
MOD L048	48″
MOD L060	60″
MOD L072	72"
MOD L120	120″

# 4. COIL WIRE LENGTH (Common options for 100 & 200 Serie type coils)